


# IF0312



## Inductive sensor

IFK2007-ARO/SL/LS-100AK RT



### Product characteristics

Output function		normally open
Sensing range	[mm]	7
Housing		threaded type
Dimensions	[mm]	M12 x 1 / L = 62

### Application

Special feature	Increased sensing range
-----------------	-------------------------

### Electrical data

Frequency AC	[Hz]	47...63
Operating voltage	[V]	20...140 AC / 10...140 DC
Protection class		I
Reverse polarity protection		no

### Outputs

Output function		normally open
Max. voltage drop switching output DC	[V]	5
Max. voltage drop switching output AC	[V]	5
Minimum load current	[mA]	5
Max. leakage current	[mA]	0.8
Permanent current rating of switching output AC	[mA]	200
Permanent current rating of switching output DC	[mA]	200
Short-time current rating of switching output	[mA]	900; (20 ms / 0,5 Hz)
Switching frequency AC	[Hz]	25
Switching frequency DC	[Hz]	90
Short-circuit proof		no
Overload protection		no

### Detection zone

Sensing range	[mm]	7
Operating distance	[mm]	0...5.7
Increased sensing range		yes

# IF0312



## Inductive sensor

IFK2007-ARO/SL/LS-100AK RT

### Accuracy / deviations

Correction factor	steel: 1 / stainless steel: 0.7 / brass: 0.4 / aluminium: 0.3 / copper: 0.2
Hysteresis [% of Sr]	3...15

### Operating conditions

Ambient temperature [°C]	-25...70
Protection	IP 67

### Tests / approvals

EMC	EN 60947-5-2	
	EN 55011	class B
MTTF [years]		1684
UL approval	Ta	0...40 °C
	Enclosure type	Type 1
	File number UL	E174191

### Mechanical data

Weight [g]	30.1
Housing	threaded type
Mounting	non-flush mountable
Dimensions [mm]	M12 x 1 / L = 62
Thread designation	M12 x 1
Materials	brass white bronze coated; PBT

### Displays / operating elements

Display	switching status	1 x LED, red
---------	------------------	--------------

### Electrical connection

Required protection	miniature fuse to IEC60127-2 sheet 1; ≤ 2 A; fast acting
---------------------	--

### Accessories

Items supplied	lock nuts: 2
----------------	--------------

### Remarks

Remarks	Recommendation: Check the safe functioning of the unit after a short circuit.
Pack quantity	1 pcs.

### Electrical connection - plug

Connector: 1 x 1/2"; coding: C




# IF0312



## Inductive sensor

IFK2007-ARO/SL/LS-100AK RT

### Connection



Note miniature fuse to IEC60127-2 sheet 1  $\leq 2$  A fast acting