



Infrared Transceiver, 9.6 kbit/s to 115.2 kbit/s (SIR) for IrDA® Applications



20206-1

DESCRIPTION

TFBS4652 is an infrared transceiver that supports data rates up to 115 kbit/s per the IrDA standard. The link distance is up to 1 meter. The transceiver includes a PIN photodiode, an infrared emitter, and a low power control IC. These components have not been qualified according to automotive specifications.

FEATURES

- Compliant to the IrDA physical layer specification
- Standard IrDA link distance of 1 m
- Low power consumption, typically less than 70 μ A
- Less than 1 μ A in shutdown mode
- Adjustable to logic I/O voltage swing from 1.5 V to 5.5 V
- Material categorization:
for definitions of compliance please see www.vishay.com/doc?99912



RoHS
COMPLIANT
HALOGEN
FREE
GREEN
(5-2008)

APPLICATIONS

- Short-distance wireless communication and data transfer
- Use in environments where RF is problematic


LINKS TO ADDITIONAL RESOURCES



DESIGN SUPPORT TOOLS

- [3D model](#)
- [Window size calculator](#)
- [Symbols and terminology](#)
- [IRDC protocol](#)
- [Reference layouts and circuit diagrams](#)

FUNCTIONAL BLOCK DIAGRAM






| PRODUCT SUMMARY | | | | | |
|-----------------|--------------------|-------------------------------------|-------------------|-----------------------|--------------------------|
| PART NUMBER | DATA RATE (kbit/s) | DIMENSIONS H x L x W (mm x mm x mm) | LINK DISTANCE (m) | OPERATING VOLTAGE (V) | IDLE SUPPLY CURRENT (mA) |
| TFBS4652 | 115.2 | 1.6 x 6.8 x 2.8 | 0 to ≥ 1 | 2.4 to 5.5 | 0.07 |

| PARTS TABLE | | |
|--------------|---|----------|
| PART | DESCRIPTION | QTY/REEL |
| TFBS4652-TR1 | Oriented in carrier tape for side view surface mounting | 1000 pcs |
| TFBS4652-TR3 | Oriented in carrier tape for side view surface mounting | 2500 pcs |
| TFBS4652-TT1 | Oriented in carrier tape for top view surface mounting | 1000 pcs |

| PIN DESCRIPTION | | | | |
|-----------------|--------------------|---|-----|--------|
| PIN NUMBER | SYMBOL | DESCRIPTION | I/O | ACTIVE |
| 1 | IREDA | IREDA anode, connected via a current limiting resistor to V _{CC2} . A separate unregulated power supply can be used. | | |
| 2 | RXD | Receiver output. Normally high, goes low for a defined pulse duration with the rising edge of the optical input signal. Output is a CMOS tri-state driver, which swings between ground and V _{logic} . Receiver echoes transmitter output. | O | Low |
| 3 | TXD | Transmitter data input. Setting this input above the threshold turns on the transmitter. This input switches the IRED with the maximum transmit pulse width of about 100 μs. | I | High |
| 4 | SD | Shutdown. Logic low at this input enables the receiver, enables the transmitter, and un-tri-states the receiver output. It must be driven high for shutting down the transceiver. | I | High |
| 5 | V _{logic} | Reference for the logic swing of the output and the input logic levels. | I | |
| 6 | V _{CC} | Power supply, 2.4 V to 5.5 V. This pin provides power for the receiver and transmitter drive section. Connect V _{CC1} via an optional filter. | | |
| 7 | GND | Ground | | |

PINOUT

TFBS4652, bottom view
weight 0.04 g





| ABSOLUTE MAXIMUM RATINGS | | | | | | |
|--|--|------------------------|-------|------|--------------------------|------|
| PARAMETER | TEST CONDITIONS | SYMBOL | MIN. | TYP. | MAX. | UNIT |
| Supply voltage range, transceiver | -0.3 V < V _{CC2} < 6 V | V _{CC1} | -0.5 | - | 6 | V |
| Supply voltage range, transmitter | -0.5 V < V _{CC1} < 6 V | V _{CC2} | -0.5 | - | 6 | V |
| Supply voltage range, digital supply | -0.5 V < V _{CC1} < 6 V | V _{logic} | -0.5 | - | 6 | V |
| Voltage at RXD | All states | V _{IN} | -0.5 | - | V _{logic} + 0.5 | V |
| Input voltage range, transmitter TXD | Independent of V _{dd} or V _{logic} | V _{IN} | -0.5 | - | 6 | V |
| Input currents | For all pins, except IRED anode pin | I _{CC} | - | - | 10 | mA |
| Output sinking current | | | - | - | 25 | mA |
| Power dissipation | | P _D | - | - | 250 | mW |
| Junction temperature | | T _J | - | - | 125 | °C |
| Ambient temperature range (operating) | | T _{amb} | -25 | - | +85 | °C |
| Storage temperature | | T _{stg} | -25 | - | +85 | °C |
| Soldering temperature | See section "Recommended Solder Profile" | | - | - | 260 | °C |
| Repetitive pulse output current | < 90 μs, t _{on} < 20 % | I _{IRED} (RP) | - | - | 430 | mA |
| Average output current (transmitter) | | I _{IRED} (DC) | - | - | 85 | mA |
| ESD protection | JESD22-A114 | V _{ESD} | 2 | - | - | kV |
| Latchup | JESD78 | | ± 100 | - | - | mA |
| Thermal resistance junction to ambient | JESD51 | R _{thJA} | - | 300 | - | K/W |

Note

- Reference point ground unless otherwise noted. Typical values are for DESIGN AID ONLY, not guaranteed nor subject to production testing

| EYE SAFETY INFORMATION | |
|---|----------------|
| STANDARD | CLASSIFICATION |
| IEC/EN 60825-1 (2007-03), DIN EN 60825-1 (2008-05) "SAFETY OF LASER PRODUCTS - Part 1: equipment classification and requirements", simplified method | Class 1 |
| IEC 62471 (2006), CIE S009 (2002) "Photobiological Safety of Lamps and Lamp Systems" | Exempt |
| DIRECTIVE 2006/25/EC OF THE EUROPEAN PARLIAMENT AND OF THE COUNCIL of 5 th April 2006 on the minimum health and safety requirements regarding the exposure of workers to risks arising from physical agents (artificial optical radiation) (19 th individual directive within the meaning of article 16(1) of directive 89/391/EEC) | Exempt |

Note

- Vishay transceivers operating inside the absolute maximum ratings are classified as eye safe according the above table



| ELECTRICAL CHARACTERISTICS ($T_{amb} = 25\text{ }^{\circ}\text{C}$, $V_{CC} = 2.4\text{ V to }5.5\text{ V}$ unless otherwise noted) | | | | | | |
|--|---|-------------|------------------------|------------------------|-------------------------|------------------|
| PARAMETER | TEST CONDITIONS | SYMBOL | MIN. | TYP. | MAX. | UNIT |
| TRANSCEIVER | | | | | | |
| Supply voltage range | | V_{CC} | 2.4 | - | 5.5 | V |
| Dynamic supply current | | | | | | |
| Idle supply current at V_{CC1} (receive mode, no signal) | SD = low, $T_{amb} = -25\text{ }^{\circ}\text{C to }+85\text{ }^{\circ}\text{C}$ independent of ambient light, $V_{CC1} = V_{CC2} = 2.4\text{ V to }5.5\text{ V}$ | I_{CC1} | 40 | 70 | 110 | μA |
| Peak supply current during transmission | SD = low, TXD = high | I_{ccpk} | - | 2 | 3 | mA |
| Idle, dark ambient at V_{logic} - pin | SD = low ($< 0.8\text{ V}$), $E_{eamb} = 0\text{ klx}$, $E_e < 4\text{ mW/m}^2$ | I_{logic} | - | - | 1 | μA |
| Shutdown supply current, dark ambient | SD = high ($> V_{logic} - 0.5\text{ V}$), $T = 25\text{ }^{\circ}\text{C}$, $E_e = 0\text{ klx}$ | I_{SD} | - | - | 0.1 | μA |
| | SD = high ($> V_{logic} - 0.5\text{ V}$), $T = 85\text{ }^{\circ}\text{C}$, $E_e = 0\text{ klx}$ | I_{SD} | - | - | 1 | μA |
| Output voltage low | $I_{OL} = 0.2\text{ mA}$, $V_{CC} = 2.4\text{ V}$, $C_{load} = 15\text{ pF}$ | V_{OL} | - | - | $0.15 \times V_{CC1}$ | V |
| Output voltage high | $I_{OL} = 0.2\text{ mA}$, $V_{CC} = 2.4\text{ V}$, $C_{load} = 15\text{ pF}$ | V_{OH} | $0.8 \times V_{logic}$ | - | - | V |
| RXD to V_{logic} pull-up impedance | SD = high ($> V_{logic} - 0.5\text{ V}$) | R_{RXD} | - | 500 | - | $\text{k}\Omega$ |
| Input voltage low (TXD, SD) | | V_{ILo} | -0.3 | - | 0.4 | V |
| Input voltage high (TXD, SD) | $V_{CC} = 2.4\text{ V to }5.5\text{ V}$ | V_{IHl} | $V_{logic} - 0.5$ | - | 6 | V |
| Input voltage threshold SD | $V_{CC} = 2.4\text{ V to }5.5\text{ V}$ | | 0.9 | $0.5 \times V_{logic}$ | $0.66 \times V_{logic}$ | V |
| Input capacitance (TXD, SD) | | C_I | - | - | 6 | pF |

Note

- Typical values are for DESIGN AID ONLY, not guaranteed nor subject to production testing



| OPTOELECTRONIC CHARACTERISTICS | | | | | | |
|---|--|----------------------------|------------------|------|------------------|-------------------|
| PARAMETER | TEST CONDITIONS | SYMBOL | MIN. | TYP. | MAX. | UNIT |
| RECEIVER | | | | | | |
| Sensitivity: minimum irradiance E_e in angular range ⁽¹⁾ | 9.6 kbit/s to 115.2 kbit/s $\lambda = 850 \text{ nm to } 900 \text{ nm}$ | E_e | - | 40 | 81 | mW/m ² |
| Maximum irradiance E_e in angular range ⁽²⁾ | $\lambda = 850 \text{ nm to } 900 \text{ nm}$ | E_e | 2 | - | - | kW/m ² |
| No output receiver input irradiance ⁽³⁾ | According to IrDA IrPHY 1.4, appendix A1, fluorescent light specification | E_e | 4 | - | - | mW/m ² |
| Rise time of output signal | 10 % to 90 %, $C_L = 15 \text{ pF}$ | $t_{r(RXD)}$ | 20 | - | 100 | ns |
| Fall time of output signal | 90 % to 10 %, $C_L = 15 \text{ pF}$ | $t_{f(RXD)}$ | 20 | - | 100 | ns |
| RXD pulse width of output signal, 50 % ⁽⁴⁾ | Input pulse width 1.63 μs | t_{PW} | 1.7 | - | 2.9 | μs |
| Receiver start up time | Power on delay | | - | 100 | 150 | μs |
| Latency | | t_L | 30 | 50 | 100 | μs |
| TRANSMITTER | | | | | | |
| IRED operating current, current controlled | The IRED current is internally controlled but also can be reduced by an external resistor R_1 ⁽⁵⁾ | I_D | 200 | 300 | 430 | mA |
| Forward voltage of built-in IRED | $I_F = 300 \text{ mA}$ | V_F | 1.4 | 1.8 | 1.9 | V |
| Output leakage IRED current | TXD = 0 V, $0 < V_{CC1} < 5.5 \text{ V}$ | I_{IRED} | -1 | 0.01 | 1 | μA |
| Output radiant intensity ⁽⁵⁾ | $a = 0^\circ, 15^\circ$, TXD = high, SD = low, $R_1 = 0 \Omega$ | I_e | 40 | 250 | 400 | mW/sr |
| Output radiant intensity | $V_{CC1} = 5 \text{ V}$, $a = 0^\circ, 15^\circ$ TXD = low or SD = high (receiver is inactive as long as SD = high) | I_e | - | - | 0.04 | mW/sr |
| Saturation voltage of IRED driver | $V_{CC} = 3 \text{ V}$, $I_F = 50 \text{ mA}$ | V_{CEsat} | - | 0.4 | - | V |
| Peak - emission wavelength | | λ_p | 870 | - | 910 | nm |
| Spectral bandwidth | | $\Delta\lambda$ | - | 45 | - | nm |
| Optical rise time, optical fall time | | t_{ropt} , t_{fopt} | 10 | 50 | 300 | ns |
| Optical output pulse duration | Input pulse width $1.6 < t_{TXD} < 23 \mu\text{s}$ | t_{opt} | $t_{TXD} - 0.15$ | - | $t_{TXD} + 0.15$ | μs |
| | Input pulse width $t_{TXD} \geq 23 \mu\text{s}$ | t_{opt} | 23 | 50 | 100 | μs |
| Optical overshoot | | | - | - | 25 | % |

Notes


- $T_{amb} = 25 \text{ }^\circ\text{C}$, $V_{CC} = 2.4 \text{ V to } 5.5 \text{ V}$ unless otherwise noted. Typical values are for design aid only, not guaranteed nor subject to production testing
- (1) IrDA sensitivity definition: minimum irradiance E_e in angular range, power per unit area. The receiver must meet the BER specification while the source is operating at the minimum intensity in angular range into the minimum half-angular range at the maximum link length
- (2) Maximum irradiance E_e in angular range, power per unit area. The optical delivered to the detector by a source operating at the maximum intensity in angular range at minimum link length must not cause receiver overdrive distortion and possible related link errors. If placed at the active output interface reference plane of the transmitter, the receiver must meet its bit error ratio (BER) specification. For more definitions see the document "Symbols and Terminology" on the Vishay website
- (3) This parameter reflects the backlight test of the IrDA physical layer specification to guarantee immunity against light from fluorescent lamps
- (4) RXD output is edge triggered by the rising edge of the optical input signal. The output pulse duration is independent of the input pulse duration
- (5) The radiant intensity can be adjusted by the external current limiting resistor to adapt the intensity to the desired value. The given value is for maximum link distance operating the transceiver without current control resistor ($R_1 = 0 \Omega$) and using the internal current control



| TRUTH TABLE | | | | |
|-------------|---------------|--|--|----------------|
| INPUTS | | | OUTPUTS | |
| SD | TXD | OPTICAL INPUT IRRADIANCE mW/m ² | RXD | TRANSMITTER |
| High | x | x | Tri-state floating with a weak pull-up to the supply voltage | 0 |
| Low | High | x | Low (echo on) | I _e |
| Low | High > 100 μs | x | High | 0 |
| Low | Low | < 2 | High | 0 |
| Low | Low | > min. irradiance E _e < max. irradiance E _e | Low (active) | 0 |
| Low | Low | > max. irradiance E _e | x | 0 |

RECOMMENDED CIRCUIT DIAGRAM

Operated at a clean low impedance power supply the TFBS4652 needs only one additional external component when the IRED drive current should be minimized for minimum current consumption according the low power IrDA standard. When combined operation in IrDA and remote control is intended no current limiting resistor is recommended. When long wires are used for bench tests, the capacitors are mandatory for testing rise/fall time correctly.



19289

Fig. 1 - Recommended Application Circuit

The capacitor C1 is buffering the supply voltage V_{CC2} and eliminates the inductance of the power supply line. This one should be a small ceramic version or other fast capacitor to guarantee the fast rise time of the IRED current. The resistor R1 is necessary for controlling the IRED drive current when the internally controlled current is too high for the application.

Vishay transceivers integrate a sensitive receiver and a built-in power driver. The combination of both needs a careful circuit board layout. The use of thin, long, resistive and inductive wiring should be avoided. The inputs (TXD, SD) and the output RXD should be directly (DC) coupled to the I/O circuit.

The capacitor C2 combined with the resistor R2 is the low pass filter for smoothing the supply voltage.

As already stated above R2, C1 and C2 are optional and depend on the quality of the supply voltages V_{CCx} and injected noise. An unstable power supply with dropping voltage during transmission may reduce the sensitivity (and transmission range) of the transceiver.

The placement of these parts is critical. It is strongly recommended to position C2 as close as possible to the transceiver power supply pins.

When extended wiring is used as in bench tests the inductance of the power supply can cause dynamically a voltage drop at V_{CC2}. Often some power supplies are not able to follow the fast current rise time. In that case another 4.7 μF (type, see table under C1) at V_{CC2} will be helpful.

Under extreme EMI conditions as placing an RF-transmitter antenna on top of the transceiver, we recommend to protect all inputs by a low-pass filter, as a minimum a 12 pF capacitor, especially at the RXD port.

RECOMMENDED APPLICATION CIRCUIT COMPONENTS

| COMPONENT | RECOMMENDED VALUE |
|-----------|---|
| C1, C2 | 0.1 μF, ceramic Vishay part# VJ 1206 Y 104 J XXMT |
| R1 | See table below |
| R2 | 47 Ω, 0.125 W (V _{CC1} = 3 V) |

I/O AND SOFTWARE

In the description, already different I/Os are mentioned. Different combinations are tested and the function verified with the special drivers available from the I/O suppliers. In special cases refer to the I/O manual, the Vishay application notes, or contact directly Vishay Sales, Marketing or Application.

For operating at RS232 ports we recommend to use an encoder / decoder-module.

Note

- TFBS4652 echoes the TXD signal at the RXD output during transmission. For communication this signal is to be correctly ignored by the controller or the software. The echo signal is implemented for test purposes in mass production



ASSEMBLY INSTRUCTIONS


Reflow Soldering

- Reflow soldering must be done within 72 h while stored under a max. temperature of 30 °C, 60 % RH after opening the dry pack envelope
- Set the furnace temperatures for pre-heating and heating in accordance with the reflow temperature profile as shown in the diagram. Exercise extreme care to keep the maximum temperature below 260 °C. The temperature shown in the profile means the temperature at the device surface. Since there is a temperature difference between the component and the circuit board, it should be verified that the temperature of the device is accurately being measured
- Handling after reflow should be done only after the work surface has been cooled off

Manual Soldering

- Use a soldering iron of 25 W or less. Adjust the temperature of the soldering iron below 300 °C
- Finish soldering within 3 s
- Handle products only after the temperature has cooled off

VISHAY LEAD (Pb)-FREE REFLOW SOLDER PROFILE





PACKAGE DIMENSIONS in millimeters




Fig. 2 - TFBS4652 Mechanical Dimensions, Tolerance ± 0.2 mm, if not Otherwise Mentioned





Fig. 3 - TFBS4652 Soldering Footprint, Tolerance ± 0.2 mm, if not Otherwise Mentioned



TAPE DIMENSIONS FOR TR1 AND TR3 in millimeters

Tape for Side View Oriented Parts



Drawing-No.: 9.700-5296.01-4


Issue: prel. copy; 24.11.04

19285



TAPE DIMENSIONS FOR TT1 in millimeters


Tape for Top View Oriented Parts



Drawing-No.: 9.700-5340.01-4
 Issue: 1; 15.01.09
 21663




REEL DIMENSIONS in millimeters



Drawing-No.: 9.800-5090.01-4
Issue: 1; 29.11.05
14017


Form of the leave open of the wheel is supplier specific.

Dimension acc. to IEC EN 60 286-3



| TAPING VARIANT | TAPE WIDTH (mm) | A MAX. (mm) | N (mm) | W ₁ MIN. (mm) | W ₂ MAX. (mm) | W ₃ MIN. (mm) | W ₃ MAX. (mm) |
|----------------|-----------------|-------------|--------|--------------------------|--------------------------|--------------------------|--------------------------|
| TT1 / TR1 | 16 | 180 | 60 | 16.4 | 22.4 | 15.9 | 19.4 |
| TT3 / TR3 | 16 | 330 | 50 | 16.4 | 22.4 | 15.9 | 19.4 |

LEADER AND TRAILER DIMENSIONS in millimeters



COVER TAPE PEEL STRENGTH

According to DIN EN 60286-3
0.1 N to 1.3 N
300 ± 10 mm/min.
165° to 180° peel angle

LABEL


Standard bar code labels for finished goods

The standard bar code labels are product labels and used for identification of goods. The finished goods are packed in final packing area. The standard packing units are labeled with standard bar code labels before transported as finished goods to warehouses. The labels are on each packing unit and contain Vishay Semiconductor GmbH specific data.



DRY PACKING

The reel is packed in an anti-humidity bag to protect the devices from absorbing moisture during transportation and storage.



FINAL PACKING

The sealed reel is packed into a cardboard box.

RECOMMENDED METHOD OF STORAGE

Dry box storage is recommended as soon as the aluminum bag has been opened to prevent moisture absorption. The following conditions should be observed, if dry boxes are not available:

- Storage temperature 10 °C to 30 °C
- Storage humidity ≤ 60 % RH max.


After more than 72 h under these conditions moisture content will be too high for reflow soldering.

In case of moisture absorption, the devices will recover to the former condition by drying under the following condition: 192 h at 40 °C + 5 °C / - 0 °C and < 5 % RH (dry air / nitrogen) or

96 h at 60 °C + 5 °C and < 5 % RH for all device containers or

24 h at 125 °C + 5 °C not suitable for reel or tubes.

An EIA JEDEC® standard J-STD-020 level 4 label is included on all dry bags.



EIA JEDEC standard J-STD-020 level 4 label is included on all dry bags

OUTER PACKAGING

The sealed reel is packed into a pizza box.

| CARTON BOX DIMENSIONS in millimeters | | | | |
|--------------------------------------|-----------------------------|-----------|-------|--------|
| <p>22127</p> | | | | |
| ORDER CODE | BOXING | THICKNESS | WIDTH | LENGTH |
| TT3 / TR3 | Pizza box (taping in reels) | 50 | 340 | 340 |
| TT1 / TR1 | Pizza box (taping in reels) | 32 | 190 | 190 |



| VISHAY SEMICONDUCTOR GmbH STANDARD BAR CODE PRODUCT LABEL (finished goods) | | |
|--|--------------|--------------|
| PLAIN WRITING | ABBREVIATION | LENGTH |
| Item-description | - | 18 |
| Item-number | INO | 8 |
| Selection-code | SEL | 3 |
| LOT-/serial-number | BATCH | 10 |
| Data-code | COD | 3 (YWW) |
| Plant-code | PTC | 2 |
| Quantity | QTY | 8 |
| Accepted by | ACC | - |
| Packed by | PCK | - |
| Mixed code indicator | MIXED CODE | - |
| Origin | xxxxxxx+ | Company logo |
| Long bar code top | Type | Length |
| Item-number | N | 8 |
| Plant-code | N | 2 |
| Sequence-number | X | 3 |
| Quantity | N | 8 |
| Total length | - | 21 |
| Short bar code bottom | Type | Length |
| Selection-code | X | 3 |
| Data-code | N | 3 |
| Batch-number | X | 10 |
| Filter | - | 1 |
| Total length | - | 17 |

ESD PRECAUTION

Proper storage and handling procedures should be followed to prevent ESD damage to the devices especially when they are removed from the antistatic shielding bag. Electrostatic sensitive devices warning labels are on the packaging.

VISHAY SEMICONDUCTORS STANDARD BAR CODE LABELS

The Vishay Semiconductors standard bar code labels are printed at final packing areas. The labels are on each packing unit and contain Vishay Semiconductors specific data.





Disclaimer

ALL PRODUCT, PRODUCT SPECIFICATIONS AND DATA ARE SUBJECT TO CHANGE WITHOUT NOTICE TO IMPROVE RELIABILITY, FUNCTION OR DESIGN OR OTHERWISE.

Vishay Intertechnology, Inc., its affiliates, agents, and employees, and all persons acting on its or their behalf (collectively, "Vishay"), disclaim any and all liability for any errors, inaccuracies or incompleteness contained in any datasheet or in any other disclosure relating to any product.

Vishay makes no warranty, representation or guarantee regarding the suitability of the products for any particular purpose or the continuing production of any product. To the maximum extent permitted by applicable law, Vishay disclaims (i) any and all liability arising out of the application or use of any product, (ii) any and all liability, including without limitation special, consequential or incidental damages, and (iii) any and all implied warranties, including warranties of fitness for particular purpose, non-infringement and merchantability.

Statements regarding the suitability of products for certain types of applications are based on Vishay's knowledge of typical requirements that are often placed on Vishay products in generic applications. Such statements are not binding statements about the suitability of products for a particular application. It is the customer's responsibility to validate that a particular product with the properties described in the product specification is suitable for use in a particular application. Parameters provided in datasheets and / or specifications may vary in different applications and performance may vary over time. All operating parameters, including typical parameters, must be validated for each customer application by the customer's technical experts. Product specifications do not expand or otherwise modify Vishay's terms and conditions of purchase, including but not limited to the warranty expressed therein.

Hyperlinks included in this datasheet may direct users to third-party websites. These links are provided as a convenience and for informational purposes only. Inclusion of these hyperlinks does not constitute an endorsement or an approval by Vishay of any of the products, services or opinions of the corporation, organization or individual associated with the third-party website. Vishay disclaims any and all liability and bears no responsibility for the accuracy, legality or content of the third-party website or for that of subsequent links.

Vishay products are not designed for use in life-saving or life-sustaining applications or any application in which the failure of the Vishay product could result in personal injury or death unless specifically qualified in writing by Vishay. Customers using or selling Vishay products not expressly indicated for use in such applications do so at their own risk. Please contact authorized Vishay personnel to obtain written terms and conditions regarding products designed for such applications.

No license, express or implied, by estoppel or otherwise, to any intellectual property rights is granted by this document or by any conduct of Vishay. Product names and markings noted herein may be trademarks of their respective owners.