

10-A, 4.75-V to 14-V INPUT, NON-ISOLATED, WIDE-OUTPUT, DIGITAL POWERTRAIN™ MODULE


Check for Samples: [PTD08A010W](#)

FEATURES

- Up to 10-A Output Current
- 4.75-V to 14-V Input Voltage
- Programmable Wide-Output Voltage (0.7 V to 3.6 V)
- Efficiencies up to 96%
- Digital I/O
 - PWM signal
 - INHIBIT
 - Current limit flag (FAULT)
 - Synchronous Rectifier Enable (SRE)
- Analog I/O
 - Temperature
 - Output current
- Safety Agency Approvals: (Pending)
 - UL/IEC/CSA-C22.2 60950-1
- Operating Temperature: –40°C to 85°C

APPLICATIONS

- Digital Power Systems using UCD9XXX Digital Controllers



DESCRIPTION

The PTD08A010W is a high-performance 10-A rated, non-isolated digital PowerTrain module. This module is the power conversion section of a digital power system which incorporates TI's UCD7230 MOSFET driver IC. The PTD08A010W must be used in conjunction with a digital power controller such as the UCD9240 or UCD9110 family. The PTD08A010W receives control signals from the digital controller and provides parametric and status information back to the digital controller. Together, PowerTrain modules and a digital power controller form a sophisticated, robust, and easily configured power management solution.

Operating from an input voltage range of 4.75 V to 14 V, the PTD08A010W provides step-down power conversion to a wide range of output voltages from, 0.7 V to 3.6 V. The wide input voltage range makes the PTD08A010W particularly suitable for advanced computing and server applications that utilize a loosely regulated 8-V, 9.6-V or 12-V intermediate distribution bus. Additionally, the wide input voltage range increases design flexibility by supporting operation with tightly regulated 5-V or 12-V intermediate bus architectures.

The module incorporates output over-current and temperature monitoring which protects against most load faults. Output current and module temperature signals are provided for the digital controller to permit user defined over-current and over-temperature warning and fault scenarios.

The module uses double-sided surface mount construction to provide a low profile and compact footprint. Package options include both through-hole and surface mount configurations that are lead (Pb) - free and RoHS compatible.



Please be aware that an important notice concerning availability, standard warranty, and use in critical applications of Texas Instruments semiconductor products and disclaimers thereto appears at the end of this data sheet.


POWERTRAIN is a trademark of Texas Instruments.



This integrated circuit can be damaged by ESD. Texas Instruments recommends that all integrated circuits be handled with appropriate precautions. Failure to observe proper handling and installation procedures can cause damage.

ESD damage can range from subtle performance degradation to complete device failure. Precision integrated circuits may be more susceptible to damage because very small parametric changes could cause the device not to meet its published specifications.

Standard PTD08A010W Application



UDG-07054

A. C₁₂ and C_{O1} are optional when the operating frequency is greater than 500 kHz.

ORDERING INFORMATION

For the most current package and ordering information, see the Package Option Addendum at the end of this datasheet, or see the TI website at www.ti.com.

DATASHEET TABLE OF CONTENTS

| DATASHEET SECTION | PAGE NUMBER |
|--|-------------|
| ENVIRONMENTAL AND ABSOLUTE MAXIMUM RATINGS | 3 |
| ELECTRICAL CHARACTERISTICS TABLE | 4 |
| TERMINAL FUNCTIONS | 5 |
| TYPICAL CHARACTERISTICS ($V_I = 12V$) | 6 |
| TYPICAL CHARACTERISTICS ($V_I = 5V$) | 8 |
| TYPICAL APPLICATION SCHEMATIC | 10 |
| GRAPHICAL USER INTERFACE VALUES | 11 |
| TRAY DRAWINGS | 12 |

ENVIRONMENTAL AND ABSOLUTE MAXIMUM RATINGS

(Voltages are with respect to GND)

| | | | | UNIT |
|------------|-----------------------------|--|---------------------------|-----------|
| V_I | Input voltage | | 16 | V |
| V_B | Bias voltage | | 16 | V |
| T_A | Operating temperature range | Over V_I range | -40 to 85 | °C |
| T_{wave} | Wave soldering temperature | Surface temperature of module body or pins for 5 seconds maximum | suffix AD 260 | |
| T_{stg} | Storage temperature | | -55 to 125 ⁽¹⁾ | G |
| | Mechanical shock | Per Mil-STD-883D, Method 2002.3, 1 msec, 1/2 sine, mounted | suffix AD 200 | |
| | Mechanical vibration | Mil-STD-883D, Method 2007.2, 20-2000 Hz | 15 | |
| | Weight | | 3.9 | grams |
| MTBF | Reliability | Per Telcordia SR-332, 50% stress, $T_A = 40^\circ\text{C}$, ground benign | 9.4 | 10^6 Hr |
| | Flammability | Meets UL94V-O | | |

(1) The shipping tray or tape and reel cannot be used to bake parts at temperatures higher than 65°C.

ELECTRICAL CHARACTERISTICS

PTD08A010W

$T_A = 25^\circ\text{C}$, $F_{\text{SW}} = 350\text{kHz}$, $V_I = 12\text{ V}$, $V_O = 3.3\text{ V}$, $V_B = V_I$, $C_{I1} = 330\ \mu\text{F}$, $C_{I2} = 22\ \mu\text{F}$ ceramic, $C_{O1} = 47\ \mu\text{F}$ ceramic, $C_{O2} = 330\ \mu\text{F}$, and $I_O = I_{O(\text{max})}$ (unless otherwise stated)


| PARAMETER | | TEST CONDITIONS | | PTD08A010W | | | UNIT | |
|-------------------|------------------------------------|---|--------------------------|--------------------|--------------------|---------------------|------|-------|
| | | | | MIN | TYP | MAX | | |
| I_O | Output current | Over V_O range | 25°C, natural convection | | 0 | 10 | A | |
| V_I | Input voltage range | Over I_O range | | 4.75 | 14 ⁽¹⁾ | | V | |
| V_{OAdj} | Output voltage adjust range | Over I_O range | | 0.7 ⁽¹⁾ | 3.6 | | V | |
| η | Efficiency | $V_I = V_B = 5\text{ V}$ $I_O = 10\text{ A}$, $f_s = 350\text{ kHz}$ | $V_O = 3.3\text{ V}$ | 95% | | | | |
| | | | $V_O = 2.5\text{ V}$ | 92% | | | | |
| | | | $V_O = 1.8\text{ V}$ | 89% | | | | |
| | | | $V_O = 1.5\text{ V}$ | 88% | | | | |
| | | | $V_O = 1.2\text{ V}$ | 86% | | | | |
| | | | $V_O = 1.0\text{ V}$ | 84% | | | | |
| V_{OPP} | V_O Ripple (peak-to-peak) | 20-MHz bandwidth | | 20 | | mV _{PP} | | |
| V_B | Bias voltage | | | 4.75 | 14 | | V | |
| V_B UVLO | Bias voltage under voltage lockout | V_B increasing | | 4.25 | 4.5 | 4.75 | V | |
| | | V_B decreasing | | 4.0 | 4.25 | 4.5 | | |
| I_B | Bias current | Inhibit (pin 8) to AGND | | Standby | | 4 | mA | |
| | | | | Switching | | 34 | | |
| V_{IH} | High-level input voltage | SRE, INH, & PWM input levels | | 2.0 | 5.5 | | V | |
| V_{IL} | Low-level input voltage | | | 0.8 | | | | |
| | PWM input | Frequency range | | 300 | 1000 | | kHz | |
| | | Pulse width limits | | 130 | | | | ns |
| | TEMP output | Range | | -40 | 125 | | °C | |
| | | Accuracy, $-40^\circ\text{C} \leq T_A \leq 85^\circ\text{C}$ | | -4 | 6 | | °C | |
| | | Slope | | 10 | | | | mV/°C |
| | | Offset, $T_A = 0^\circ\text{C}$ | | 500 | | | | mV |
| V_{OH} | FAULT output | High-level output voltage, $I_{\text{FAULT}} = 4\text{ mA}$ | | 2.7 | 3.3 | | V | |
| V_{OL} | | Low-level output voltage, $I_{\text{FAULT}} = 4\text{ mA}$ | | 0 | 0.6 | | | |
| I_{LIM} | | Overcurrent threshold; Reset, followed by auto-recovery | | 20 | | A | | |
| | IOUT output | Range | | 0.15 | 3.5 | | V | |
| | | Gain | | 70 | 100 | 130 | mV/A | |
| | | Offset, $I_O = 0\text{ A}$, $V_O = 1.2\text{ V}$ | | 0.44 | 0.6 | 0.76 | V | |
| | | Output Impedance | | 10 | 15 | 21 | kΩ | |
| C_I | External input capacitance | Nonceramic | | 330 ⁽²⁾ | | μF | | |
| | | Ceramic | | 22 ⁽²⁾ | | | | |
| C_O | External output capacitance | Capacitance Value | | Nonceramic | 330 ⁽³⁾ | 5000 ⁽⁴⁾ | μF | |
| | | | | Ceramic | | 47 ⁽³⁾ | | (3) |
| | | Equivalent series resistance (non-ceramic) | | 1 ⁽⁵⁾ | | | | mΩ |

- (1) The maximum input voltage is duty cycle limited to $(V_O / (130\text{ns} \times F_{\text{SW}}))$ or 14 V, whichever is less. The maximum allowable input voltage is a function of switching frequency.
- (2) A 22 μF ceramic input capacitor is required for proper operation. An additional 330 μF bulk capacitor rated for a minimum of 500mA rms of ripple current is recommended. When operating at frequencies > 500kHz the 22 μF ceramic capacitor is only recommended. Refer to the UCD9240 controller datasheet and user interface for application specific capacitor specifications.
- (3) A 47 μF ceramic output capacitor is required for basic operation. An additional 330 μF bulk capacitor is recommended for improved transient response. When operating at frequencies > 500kHz the 47 μF ceramic capacitor is only recommended. Refer to the UCD9240 controller datasheet and user interface for application specific capacitor specifications.
- (4) 5,000 μF is the calculated maximum output capacitance given a 1V/msec output voltage rise time. Additional capacitance or increasing the output voltage rise rate may trigger the overcurrent threshold at start-up. Refer to the UCD9240 controller datasheet and user interface for application specific capacitor specifications.
- (5) This is the minimum ESR for all non-ceramic output capacitance. Refer to the UCD9240 controller datasheet and user interface for application specific capacitor specifications.

TERMINAL FUNCTIONS

| TERMINAL | | DESCRIPTION |
|--------------------|-----|--|
| NAME | NO. | |
| V _I | 1 | The positive input voltage power node to the module, which is referenced to common GND. |
| GND | 2 | This is the common ground connection for the V _I and V _O power connections. |
| | 3 | |
| V _O | 4 | The regulated positive power output with respect to GND. |
| TEMP | 5 | Temperature sense output. The voltage level on this pin represents the temperature of the module. |
| IOUT | 6 | Current sense output. The voltage level on this pin represents the average output current of the module. |
| AGND | 7 | Analog ground return. It is the 0 V _{dc} reference for the control inputs. |
| INH ⁽¹⁾ | 8 | The inhibit pin is a negative logic input that is referenced to AGND. Applying a low-level signal to this pin disables the module and turns off the output voltage. A 10 kΩ pull-up to 3.3 V or 5 V is required if the INH signal is not used. |
| FAULT | 9 | Current limit flag. The Fault signal is a 3.3 V digital output which is latched high after an over-current condition. The Fault is reset after two complete PWM cycles without an over-current condition (third rising edge of the PWM). |
| SRE | 10 | Synchronous Rectifier Enable. This pin is a high impedance digital input. A 3.3 V or 5 V logic level signals is used to enable the synchronous rectifier switch. When this signal is high, the module will source and sink output current. When this signal is low, the module will only source current. |
| PWM | 11 | This is the PWM input pin. It is a high impedance digital input that accepts 3.3 V or 5 V logic level signals up to 1 MHz. |
| VBIAS | 12 | Bias voltage supply required to power internal circuitry. For optimal performance connect VBIAS to V _I . |

(1) Denotes negative logic: High = Normal operation, Low = Function active



TYPICAL CHARACTERISTICS ($V_I = 12\text{ V}$) ⁽¹⁾

EFFICIENCY vs LOAD CURRENT




Figure 1.

EFFICIENCY vs LOAD CURRENT




Figure 2.

EFFICIENCY vs LOAD CURRENT




Figure 3.

EFFICIENCY vs LOAD CURRENT




Figure 4.

POWER DISSIPATION vs LOAD CURRENT




Figure 5.

POWER DISSIPATION vs LOAD CURRENT




Figure 6.

POWER DISSIPATION vs LOAD CURRENT




Figure 7.

POWER DISSIPATION vs LOAD CURRENT




Figure 8.

INPUT BIAS CURRENT vs SWITCHING FREQUENCY




Figure 9.

(1) The electrical characteristic data has been developed from actual products tested at 25°C. This data is considered typical for the converter.

TYPICAL CHARACTERISTICS ($V_I = 12\text{ V}$)
Safe Operating Area ⁽¹⁾

AMBIENT TEMPERATURE vs LOAD CURRENT




Figure 10.

AMBIENT TEMPERATURE vs LOAD CURRENT




Figure 11.

AMBIENT TEMPERATURE vs LOAD CURRENT




Figure 12.

AMBIENT TEMPERATURE vs LOAD CURRENT




Figure 13.

AMBIENT TEMPERATURE vs LOAD CURRENT




Figure 14.

(1) The temperature derating curves represent the conditions at which internal components are at or below the manufacturer's maximum operating temperatures. Derating limits apply to modules soldered directly to a 100 mm x 100 mm double-sided PCB with 2 oz. copper. Please refer to the mechanical specification for more information.

TYPICAL CHARACTERISTICS ($V_I = 5\text{ V}$) ⁽¹⁾




Figure 15.




Figure 16.




Figure 17.




Figure 18.




Figure 19.




Figure 20.




Figure 21.




Figure 22.




Figure 23.

(1) The electrical characteristic data has been developed from actual products tested at 25°C. This data is considered typical for the converter.

TYPICAL CHARACTERISTICS ($V_I = 5\text{ V}$)
Safe Operating Area ⁽¹⁾

AMBIENT TEMPERATURE vs LOAD CURRENT




Figure 24.

AMBIENT TEMPERATURE vs LOAD CURRENT




Figure 25.

AMBIENT TEMPERATURE vs LOAD CURRENT




Figure 26.

AMBIENT TEMPERATURE vs LOAD CURRENT




Figure 27.

(1) The temperature derating curves represent the conditions at which internal components are at or below the manufacturer's maximum operating temperatures. Derating limits apply to modules soldered directly to a 100 mm x 100 mm double-sided PCB with 2 oz. copper. Please refer to the mechanical specification for more information.

APPLICATION INFORMATION

Digital Power




Figure 28. Typical Application Schematic

B. This discrete bias power circuit may be substituted with a low dropout regulator (LDO). For example, [TPS715A33](#) can provide bias power to the UCD9240.

Figure 28 shows the UCD9240 power supply controller working in a system which requires the regulation of four independent power supplies. The loop for each power supply is created by the respective voltage outputs feeding into the Error ADC differential inputs, and completed by DPWM outputs feeding into the UCD7230 drivers which are shown on the PTD08A0x0W modules.

UCD9240 Graphical User Interface (GUI)

When using the UCD9240 digital controller along with digital PowerTrain modules to design a digital power system, several internal parameters of the modules are required to run the Fusion Digital Power Designer GUI. See the plant parameters below for the PTD08A010W and PTD08A020W digital PowerTrain modules.

Table 1. PTD08A010W Plant Parameters

| PTD08A010W Plant Parameters | | | |
|-----------------------------|-------------------|-------------------------|-------------------------|
| L (μ H) | DCR (m Ω) | Rds-on-hi (m Ω) | Rds-on-lo (m Ω) |
| 0.90 | 2.2 | 3.6 | 3.6 |

Table 2. PTD08A020W Plant Parameters

| PTD08A020W Plant Parameters | | | |
|-----------------------------|-------------------|-------------------------|-------------------------|
| L (μ H) | DCR (m Ω) | Rds-on-hi (m Ω) | Rds-on-lo (m Ω) |
| 1.0 | 1.5 | 5.0 | 2.5 |

Internal output capacitance is present on the digital PowerTrain modules themselves. When using the GUI interface this capacitance information must be included along with any additional external capacitance. See the capacitor parameters below for the PTD08A010W and PTD08A020W digital PowerTrain modules.

Table 3. PTD08A010W Capacitor Parameters

| PTD08A010W Capacitor Parameters | | | |
|---------------------------------|-------------------|----------|----------|
| C (μ F) | ESR (m Ω) | ESL (nH) | Quantity |
| 47 | 1.5 | 2.5 | 1 |

Table 4. PTD08A020W Capacitor Parameters

| PTD08A020W Capacitor Parameters | | | |
|---------------------------------|-------------------|----------|----------|
| C (μ F) | ESR (m Ω) | ESL (nH) | Quantity |
| 47 | 1.5 | 2.5 | 2 |

PACKAGING INFORMATION

| Orderable part number | Status (1) | Material type (2) | Package Pins | Package qty Carrier | RoHS (3) | Lead finish/ Ball material (4) | MSL rating/ Peak reflow (5) | Op temp (°C) | Part marking (6) |
|------------------------------|---------------|----------------------|-----------------------------------|-----------------------|-------------|--------------------------------------|--|--------------|---------------------|
| PTD08A010WAD | Active | Production | Through-Hole Module (EGS) 12 | 36 TIW TRAY | In-Work | SN | Level-1-235C-UNLIM/ Level-3-260C-168HRS | -40 to 85 | |
| PTD08A010WAD.B | Active | Production | Through-Hole Module (EGS) 12 | 36 TIW TRAY | In-Work | SN | Level-1-235C-UNLIM/ Level-3-260C-168HRS | -40 to 85 | |

(1) **Status:** For more details on status, see our [product life cycle](#).

(2) **Material type:** When designated, preproduction parts are prototypes/experimental devices, and are not yet approved or released for full production. Testing and final process, including without limitation quality assurance, reliability performance testing, and/or process qualification, may not yet be complete, and this item is subject to further changes or possible discontinuation. If available for ordering, purchases will be subject to an additional waiver at checkout, and are intended for early internal evaluation purposes only. These items are sold without warranties of any kind.

(3) **RoHS values:** Yes, No, RoHS Exempt. See the [TI RoHS Statement](#) for additional information and value definition.

(4) **Lead finish/Ball material:** Parts may have multiple material finish options. Finish options are separated by a vertical ruled line. Lead finish/Ball material values may wrap to two lines if the finish value exceeds the maximum column width.

(5) **MSL rating/Peak reflow:** The moisture sensitivity level ratings and peak solder (reflow) temperatures. In the event that a part has multiple moisture sensitivity ratings, only the lowest level per JEDEC standards is shown. Refer to the shipping label for the actual reflow temperature that will be used to mount the part to the printed circuit board.

(6) **Part marking:** There may be an additional marking, which relates to the logo, the lot trace code information, or the environmental category of the part.

Multiple part markings will be inside parentheses. Only one part marking contained in parentheses and separated by a "~" will appear on a part. If a line is indented then it is a continuation of the previous line and the two combined represent the entire part marking for that device.


Important Information and Disclaimer: The information provided on this page represents TI's knowledge and belief as of the date that it is provided. TI bases its knowledge and belief on information provided by third parties, and makes no representation or warranty as to the accuracy of such information. Efforts are underway to better integrate information from third parties. TI has taken and continues to take reasonable steps to provide representative and accurate information but may not have conducted destructive testing or chemical analysis on incoming materials and chemicals. TI and TI suppliers consider certain information to be proprietary, and thus CAS numbers and other limited information may not be available for release.

In no event shall TI's liability arising out of such information exceed the total purchase price of the TI part(s) at issue in this document sold by TI to Customer on an annual basis.

MECHANICAL DATA

EGS (R-PDSS-T12)

DOUBLE SIDED MODULE



4209187/C 02/10

- NOTES:
- A. All linear dimensions are in inches (mm).
 - B. This drawing is subject to change without notice.
 - C. 2 place decimals are ± 0.030 ($\pm 0,76$ mm).
 - D. 3 place decimals are ± 0.010 ($\pm 0,25$ mm).
 - E. Recommended keep out area for user components.
 - F. Pins are 0.040" (1,02) diameter with 0.070" (1,78) diameter standoff shoulder.
 - G. Header pins are 0.016 (0,40) SQ.
 - H. All pins: Material - Copper Alloy
Finish - Tin (100%) over Nickel plate

IMPORTANT NOTICE AND DISCLAIMER

TI PROVIDES TECHNICAL AND RELIABILITY DATA (INCLUDING DATA SHEETS), DESIGN RESOURCES (INCLUDING REFERENCE DESIGNS), APPLICATION OR OTHER DESIGN ADVICE, WEB TOOLS, SAFETY INFORMATION, AND OTHER RESOURCES "AS IS" AND WITH ALL FAULTS, AND DISCLAIMS ALL WARRANTIES, EXPRESS AND IMPLIED, INCLUDING WITHOUT LIMITATION ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE OR NON-INFRINGEMENT OF THIRD PARTY INTELLECTUAL PROPERTY RIGHTS.

These resources are intended for skilled developers designing with TI products. You are solely responsible for (1) selecting the appropriate TI products for your application, (2) designing, validating and testing your application, and (3) ensuring your application meets applicable standards, and any other safety, security, regulatory or other requirements.

These resources are subject to change without notice. TI grants you permission to use these resources only for development of an application that uses the TI products described in the resource. Other reproduction and display of these resources is prohibited. No license is granted to any other TI intellectual property right or to any third party intellectual property right. TI disclaims responsibility for, and you will fully indemnify TI and its representatives against, any claims, damages, costs, losses, and liabilities arising out of your use of these resources.

TI's products are provided subject to [TI's Terms of Sale](#) or other applicable terms available either on [ti.com](https://www.ti.com) or provided in conjunction with such TI products. TI's provision of these resources does not expand or otherwise alter TI's applicable warranties or warranty disclaimers for TI products.

TI objects to and rejects any additional or different terms you may have proposed.

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265
Copyright © 2025, Texas Instruments Incorporated