

# sanwa®

## TOKYO JAPAN

### ANALOG MULTITESTER

# TA55



### APPLICATIONS AND FEATURES

This instrument is a portable multitester designated for the measurement of low-voltage circuit.

This is used at small communications equipments, home electric appliances, voltage of lump line, and measurement of various types of batteries.

- 30A range for automotive
- High level panel visibility
- Continuity check buzzer
- Tilt-stand
- Measurable upto DC30A / DC300A with optional clamp probe (Clamp probe : CL33DC)

### SPECIFICATIONS

	Measuring range	Accuracy
DCV	0.3/3/16/30/60V(20kΩ/V)	±3% of full scale
ACV	30/120/300V(9kΩ/V)	±4% of full scale
DCA	0.5/3/30A	±5% of full scale
Resistance	2k/20k/200k/2MΩ	±3% of arc
continuity	Buzzer sounds at less than approx. 70Ω. Open voltage : 3V	

Meter type	Taut-band meter
AC rectifier form	Half-wave rectification
Accuracy assurance temperature / humidity	23±2°C 75%RH max.
Operating temperature / humidity	No condensation
Storage temperature / humidity	3~43°C, 80%RH(Max). No condensation
Bandwidth	-10 to 50°C, 70% RH or less, No Condensation
Battery	40Hz~5kHz
Fuse	R6P x 2
Size / Mass	Φ6.3 x 30mm(250V / 3A) Breaking capacity 300A fast-blow fuse
Standard accessories included	H142 x W97 x D38mm / approx.300g
	Test lead(TL-91), Instruction manual

A battery for monitoring has been installed prior to shipment from the factory. It may be discharged before the expiration of the described battery life. This battery is used to check the functions and performance of the product. Specifications and external appearance of the product described above may be revised for modification without prior notice.

# sanwa®

SANWA ELECTRIC INSTRUMENT CO., LTD.

Dempa Bldg, 4-4 Sotokanda 2-Chome, Chiyoda-Ku, Tokyo 101-0021 Japan  
Tel:+81-3-3251-0941 Fax:+81-3-3256-9740

[www.sanwa-meter.co.jp](http://www.sanwa-meter.co.jp)

Distributed by