


Product data sheet

Specifications

SQUARE D



Overload Relay, Type S, melting alloy, replacement overload, NEMA size 3, 3 pole, 3 phase, 90A, 600VAC

9065SDO12

Product availability: Stock - Normally stocked in distribution facility

Main

Range of Product	Replacement Relay
Product destination	Starter
Thermal overload type	Melting alloy

Complementary

NEMA size	3
Phase	3 phase
Number of thermal units required	3
Mounting Support	Mounting plate
[Ue] rated operational voltage	600 V AC
Height	5.6 in (142 mm)
Width	5.3 in (134.9 mm)
Depth	5.7 in (145.8 mm)

Ordering and shipping details

Category	US10CP121661
Discount Schedule	0CP1
GTIN	785901788539
Returnability	Yes
Country of origin	MX

Packing Units

Unit Type of Package 1	PCE
Nbr. of units in pkg.	1
Package 1 Height	6.70 in (17.018 cm)
Package 1 Width	6.60 in (16.764 cm)
Package 1 Length	9.40 in (23.876 cm)
Package weight(Lbs)	2.551 lb(US) (1.157 kg)

Contractual warranty

Warranty	18 months
----------	-----------

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications

Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Use Better

 Materials and Substances	
Packaging made with recycled cardboard	No
Packaging without single use plastic	No
EU RoHS Directive	Not compliant
California proposition 65	WARNING: This product can expose you to chemicals including: Lead and lead compounds, which is known to the State of California to cause cancer and birth defects or other reproductive harm. For more information go to www.P65Warnings.ca.gov

Use Again

 Repack and remanufacture	
Take-back	No