

Product data sheet

Specifications

SQUARE D



NEMA Motor Starter and contactor, Type S, auxiliary contact, 1 NC contact, internal, nonconvertible

9999SX12

Product availability: Stock - Normally stocked in distribution facility

Main

Product Range	Type S
Component type	Auxiliary Contact Module
Used with	contactor starter

Complementary

NEMA size	1 0 00 2
Auxiliary contact composition	1 NC
[Uc] control circuit voltage	<= 600 V AC 50/60 Hz
Rated breaking capacity	3 A 120 V AC inductive control circuit UL 508 1.5 A 240 V AC inductive control circuit UL 508 0.75 A 480 V AC inductive control circuit UL 508 0.6 A 600 V AC inductive control circuit UL 508 5 A <= 600 V AC resistive control circuit UL 508

Environment

Product Certifications	CSA UL Recognized UL Listed
------------------------	-----------------------------------

Ordering and shipping details

Category	US10CP121761
Discount Schedule	0CP1
GTIN	785901879732
Returnability	Yes
Country of origin	MX

Packing Units

Unit Type of Package 1	PCE
Nbr. of units in pkg.	1
Package 1 Height	1.30 in (3.302 cm)
Package 1 Width	2.30 in (5.842 cm)
Package 1 Length	3.00 in (7.62 cm)

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.

Package weight(Lbs) 1.120 oz (31.752 g)

Contractual warranty

Warranty 18 months

Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Use Better

 Materials and Substances	
Packaging made with recycled cardboard	No
Packaging without single use plastic	No
EU RoHS Directive	Not compliant
California proposition 65	WARNING: This product can expose you to chemicals including: Lead and lead compounds, which is known to the State of California to cause cancer and birth defects or other reproductive harm. For more information go to www.P65Warnings.ca.gov

Use Again

 Repack and remanufacture	
Take-back	No
WEEE Label	 The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins.

Technical Illustration

Dimensions

